Xpress

This product is mounted above or below a worksurface. It is used to provide quick power, data and USB access.

#### WHAT'S INCLUDED

1 power cube, 1 twistable attachment ring (as specified) or underworkurface bracket and hardware (as specified).

#### WHAT'S EXCLUDED

Square Grommet.

#### **NOTES**

When installed on worksurface, the Power Cube must be installed in Square Grommet Ring (Q). However, the grommet style option is **not** included and must be specified on worksurface to allow Power Cube installation.

When installed Under Worksurface (U), the Power Cube must be installed with underworksurface bracket and hardware.

The underworksurface bracket will match the case and front finish.


Data Faceplate not included (if specified).

USB Outlet has one USB-A port (10 watts max) and one USB-C port (15 watts max) for charging only. Limit of 18 watts combined output at 5 Volts DC.

Power cord is a grey cloth covered type.

Not all finishes are available in Xpress, Please see Xpress catalogue and/or specification software for details.

# T H E W P C Power Cube



**Dual Configuration** 

Quad Configuration

# PRODUCT OPTIONS

Configuration	Mounting Option	Power Cord Length (Inches)	Country of Installation	Case and Front Finish
<b>D101</b> Dual – 1 Power / 0 USB / 1 Data	Q Square Grommet	120, 180	A Canada/U.S.A.	Foundation
<b>D120</b> Dual – 1 Power / 2 USB / 0 Data	(Not Included) (Shown)			Mica
<b>D200</b> Dual – Power Only	U Under Worksurface			Accent
<b>Q202</b> Quad – 2 Power / 0 USB / 2 Data				
<b>Q221</b> Quad – 2 Power / 2 USB / 1 Data				
<b>Q240</b> Quad – 2 Power / 4 USB / 0 Data				
<b>Q320</b> Quad – 3 Power / 2 USB / 0 Data				

## SAMPLE ORDER CODE

THEWPC D101	Q	120	A	E
-------------	---	-----	---	---

# DIMENSIONS INCHES / MM

## **PRICING**

L
120 / 3048
180 / 4572
100 / 4)/2

SQUARE GROMMET MOUNTING OPTION (Q)							
CONFIGURATIO	N						
D101	D120	D200	Q202	Q221	Q240	Q320	
369	461	338	521	612	705	548	
451	544	422	604	698	790	631	

	UNDER WORKSURFACE MOUNTING OPTION (U)							
	CONFIGURATION							
	D101	D120	D200	Q202	Q221	Q240	Q320	
120 / 3048	473	564	444	623	715	811	652	
180 / 4572	558	650	529	708	802	894	737	